

making connections beautifully

Wiring Accessories • Smart Lighting Control • Wireless Audio

74C1X40

Hartland CFX Satin Steel Effect 1x400W Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer Satin Steel

| Item Image | Wiring Dimensions | | |
|-------------------------------|--|----------|--|
| | Dimmer Wiring Lee Report Lee Report Lee Way Switching Dimmer Loop Is Loop Cut. Two Way Switching Lee Way Switching Dimmer Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer 86.0 86.0 86.0 86.0 86.0 86.0 86.0 | | |
| Primary Range | Hartland CFX | | |
| Insert Type | 1 gang 400W Resistive Leading Edge Push On/Off Rotary 2 Way Switching Dimmer | | |
| Plate Finish | Hartland CFX Satin Steel Effect | | |
| Insert Colour | Satin Steel | | |
| EAN13 Barcode | 5017504269418 | | |
| Commodity Code | 85365015 | | |
| Luckins TSI | 388238109 | | |
| ETIM Class | EC000025 | | |
| Dimensions (Nominal) | Single: Height = 86.0mm Width = 86.0mm Depth = 5.0mm | | |
| Weight | 196 GR | | |
| Fixing Hole Centres | Box Fixing = 60.3mm Grid Fixing = CFX Clips | | |
| Minimum Wall Box Depth | 35mm | | |
| Wattage | 400W | | |
| Switched Poles | Single | | |
| Current Rating | 1.66 Amp | | |
| Voltage | 230V AC | \neg | |
| Maximum Load | 400W resistive Max Load | | |
| Mains Frequency | 50Hz | | |
| IP Rating | IP2XD | | |
| Contact Gap Minimum | N/A | | |
| Terminal Capacity 1 | 2x1mm² | \neg | |
| Terminal Capacity 2 | 2x1.5mm ² | | |
| Earth Terminal Capacity 1 | 5x1mm² | | |
| Earth Terminal Capacity 2 | 4 x 1.5mm2 | \neg | |
| Earth Terminal Capacity 3 | 3 x 2.5mm2 | | |
| Earth Terminal Capacity 4 | 1 x 4mm2 Multi-strand | | |
| Earth Terminal Capacity 5 | 1 x 6mm2 | | |
| Product Class 1 | Face plate must be earthed | \dashv | |
| Ambient Operating Temperature | -5° to +40°C | _ | |
| Recommended Location | Internal Use Only | | |
| Maximum Installation Altitude | 2000m | | |
| Standard/Approval | BS EN 60669-2-1 | | |
| Additional Notes | Tungsten filament GU10 lamps must be branded with a fuse base. When using mains voltagehalogen lamps- dimmers should be de-rated by 25%. When dimming LED lamps de-rated by 75% - please contact our Technical for compatibilit | у. | |



SL

making connections beautifully

Wiring Accessories • Smart Lighting Control • Wireless Audio

74C1X40

| Hartland CFX Satin Steel Effect 1X4001 | /v Resistive Leading Edge Push On-Off Rota | ary 2 way Switching Dimmer Satin Steel |
|---|--|---|
| Patents and Trademarks | CFX is a Registered Trade Mark No 2398667 Hartland CFX is a Registered Design under Reference Nos. R21 = 3023446 SS2 = 3023445 | |
| All products listed conform to current British or European standard and the product information is correct at the time of going to press. | All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System. | It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice. |
| Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding. | Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes. | Correct as at 05 July 2022 08:52 AM E&OE |

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088
E: info@hamilton-litestat.com www.hamilton-litestat.com

Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB Registered in London No. 941624 VAT Registration No. 222 6607 84









