

making connections beautifully

Wiring Accessories • Smart Lighting Control • Wireless Audio

79C1X2V

Item Image	Wiring	Dimensions		
	LOOP IN LOOP OUT TWO MAY SWITCHING METURAL COLUMN TO A SWITCHING LOOP IN LOOP OUT TWO MAY SWITCHING LOOP OUT TW	Hamilton HARTLAND CFX 1/2V Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer		
		96.0 - 5.0 - 27.5 27.5		
Primary Range	Hartland CFX	Hartland CFX		
Insert Type	1 gang 200VA Inductive Leading Edge Push On/Off Rotary 2	1 gang 200VA Inductive Leading Edge Push On/Off Rotary 2 Way Switching Dimmer		
Plate Finish	Hartland CFX Antique Brass			
Insert Colour	Antique Brass			
EAN13 Barcode	5017504299118			
Commodity Code	85365015			
Luckins TSI	388241659			
ETIM Class	EC000025			
Dimensions (Nominal)	Single: Height = 86.0mm Width = 86.0mm Depth = 5.0mi			
Weight	223 GR			
Fixing Hole Centres	Box Fixing = 60.3mm Grid Fixing = CFX Clips	Box Fixing = 60.3mm Grid Fixing = CFX Clips		
Minimum Wall Box Depth	35mm			
Wattage	200VA (low voltage)	200VA (low voltage)		
Switched Poles	Single			
Current Rating	0.8 Amp			
Voltage	220/250V AC	·		
Maximum Load	200VA (low voltage) Min Load 25VA	200VA (low voltage) Min Load 25VA		
Mains Frequency	50Hz			
IP Rating	IP2XD			
Contact Gap Minimum	None			
Terminal Capacity 1	2x1mm²			
Terminal Capacity 2	2x1.5mm²			
Earth Terminal Capacity 1	5x1mm²			
Earth Terminal Capacity 2	4 x 1.5mm2			
Earth Terminal Capacity 3	3 x 2.5mm2			
Earth Terminal Capacity 4	1 x 4mm2 Multi-strand			
Earth Terminal Capacity 5	1 x 6mm2			
Product Class 1	Face plate must be earthed			
Ambient Operating Temperature	-5° to +40°C			
Recommended Location	Internal Use Only			
Maximum Installation Altitude	2000m	·		
Standard/Approval	BS EN 60669-1			
Additional Notes	LEADING EDGE TECHNOLOGY DIMMERS for use with low dimming LED lamps de-rated by 75% - please contact our Te	LEADING EDGE TECHNOLOGY DIMMERS for use with low voltage toroidal transformers and some LED lamps. When dimming LED lamps de-rated by 75% - please contact our Technical for compatibility. NOTE: It is recommended to contact the manufacturer of the transformer to confirm that it is dimmable and is considered to be an inductive load.		



SL

making connections beautifully

Wiring Accessories • Smart Lighting Control • Wireless Audio

79C1X2V

Hartland CEX Antique Brass 1 gang 200VA Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer Antique Brass

	faritand CFX Antique Brass I gang 2007A inductive Leading Edge Push On-Oil Rolary 2 way Switching Dinnier Antique Brass		
	Patents and Trademarks	CFX is a Registered Trade Mark No 2398667 Hartland CFX is a Registered Design under Reference Nos. R21 = 3023446 SS2 = 3023445	
	All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
	Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.	Correct as at 05 July 2022 08:56 AM E&OE

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088
E: info@hamilton-litestat.com www.hamilton-litestat.com

Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB Registered in London No. 941624 VAT Registration No. 222 6607 84









