

making connections beautifully

Wiring Accessories • Smart Lighting Control • Wireless Audio

79C3X40

Hartland CFX Antique Brass 3x400W Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmers Antique Brass

	esistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmers Antique Brass		
Item Image	Wiring Dimensions		
	Dimmer Wiring Use Toleyor a Loop In Loop Dut. Two Way Switching Loop In Loop Dut. T		
Primary Range	Hartland CFX		
Insert Type	3 gang 400w Resistive Leading Edge Push On/Off Rotary 2 Way Switching Dimmer		
Plate Finish	Hartland CFX Antique Brass		
Insert Colour	Antique Brass		
EAN13 Barcode	5017504299439		
Commodity Code	85365015		
Luckins TSI	388241701		
ETIM Class	EC000025		
Dimensions (Nominal)	Double: Height = 86.0mm Width = 145.0mm Depth = 5.0mm		
Weight	443 GR		
Fixing Hole Centres	Box Fixing = 120.6mm Grid Fixing = CFX Clips		
Minimum Wall Box Depth	35mm		
Wattage	400W per gang		
Switched Poles	Single		
Current Rating	1.66 Amps per gang		
Voltage	230V AC		
Maximum Load	400W resistive per gang		
Mains Frequency	50Hz		
IP Rating	IP2XD		
Contact Gap Minimum	N/A		
Terminal Capacity 1	2x1mm²		
Terminal Capacity 2	2x1.5mm²		
Earth Terminal Capacity 1	5x1mm²		
Earth Terminal Capacity 2	4 x 1.5mm2		
Earth Terminal Capacity 3	3 x 2.5mm2		
Earth Terminal Capacity 4	1 x 4mm2 Multi-strand		
Earth Terminal Capacity 5	1 x 6mm2		
Product Class 1	Face plate must be earthed		
Ambient Operating Temperature	-5° to +40°C		
Recommended Location	Internal Use Only		
Maximum Installation Altitude	2000m		
Standard/Approval	BS EN 60669-2-1		
ditional Notes Tungsten filament GU10 lamps must be branded with a fuse base. When using mains voltagehalogen lamps- dimmers should be de-rated by 25%. When dimming LED lamps de-rated by 75% - please contact our Technical for compatibility.			



SL

making connections beautifully

Wiring Accessories • Smart Lighting Control • Wireless Audio

79C3X40

Hartland CEX Antique Brass 3x400W Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmers Antique Brass

	Hartiand CFX Antique Brass 3x400W Resistive Leading Edge Push On-On Rotary 2 Way Switching Diffiniers Antique Brass		
	Patents and Trademarks	CFX is a Registered Trade Mark No 2398667 Hartland CFX is a Registered Design under Reference Nos. R21 = 3023446 SS2 = 3023445	
	All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
	Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.	Correct as at 05 July 2022 08:56 AM E&OE

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088
E: info@hamilton-litestat.com www.hamilton-litestat.com

Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB Registered in London No. 941624 VAT Registration No. 222 6607 84









