




77C4XTSBC-B

Hartland CFX Bright Chrome 4 gang Multi-Way Touch Slave Controller Bright Chrome/Black

| Item Image | Wiring | Dimensions |
|---|--|---|
|  |  |  |
| Primary Range | Hartland CFX | |
| Insert Type | 4 gang Multi-Way Touch Slave Controller | |
| Plate Finish | Hartland CFX Bright Chrome | |
| Insert Colour | Bright Chrome/Black | |
| EAN13 Barcode | 5017504009984 | |
| Commodity Code | 85363010 | |
| Luckins TSI | 391560424 | |
| ETIM Class | EC000025 | |
| Dimensions (Nominal) | Double: Height = 86.0mm Width = 145.0mm Depth = 5.0mm | |
| Fixing Hole Centres | Box Fixing = 120.6mm Grid Fixing = CFX Clips | |
| Minimum Wall Box Depth | 35mm | |
| Wattage | The same as Touch Master or Ceiling Dimmer | |
| Switched Poles | N/A | |
| Current Rating | The same as Touch Master or Ceiling Dimmer | |
| Voltage | 220/250V AC | |
| Maximum Load | The same as Touch Master | |
| Mains Frequency | 50Hz | |
| IP Rating | IP2XD | |
| Contact Gap Minimum | N/A | |
| Terminal Capacity 1 | 2x1mm² | |
| Terminal Capacity 2 | 2x1.5mm² | |
| Earth Terminal Capacity 1 | 5x1mm² | |
| Earth Terminal Capacity 2 | 4 x 1.5mm² | |
| Earth Terminal Capacity 3 | 3 x 2.5mm² | |
| Earth Terminal Capacity 4 | 1 x 4mm² Multi-strand | |
| Earth Terminal Capacity 5 | 1 x 6mm² | |
| Product Class 1 | Face plate must be earthed | |
| Ambient Operating Temperature | -5° to +40°C | |
| Recommended Location | Internal Use Only | |
| Maximum Installation Altitude | 2000m | |
| Standard/Approval | BS EN 60669-2-1 | |
| Additional Notes | Tungsten filament GU10 lamps must be branded with a fuse base. When using mains voltage halogen lamps- dimmers should be de-rated by 25%. When using mains voltage halogen load transformer - maximum rating is 210VA. To only be used with Touch Master Dimmers | |

77C4XTSBC-B

Hartland CFX Bright Chrome 4 gang Multi-Way Touch Slave Controller Bright Chrome/Black

| | | |
|---|---|---|
| Patents and Trademarks | CFX is a Registered Trade Mark No 2398667 Hartland CFX is a Registered Design under Reference Nos. R21 = 3023446 SS2 =3023445 | |
| All products listed conform to current British or European standard and the product information is correct at the time of going to press. | All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System. | It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice. |
| Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding. | Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes. | Correct as at 05 July 2022 08:54 AM E&OE |

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088

E: info@hamilton-litestat.com www.hamilton-litestat.com

Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB
Registered in London No. 941624 VAT Registration No. 222 6607 84



Listed in **Trimble**
LUCKINS

