Hamilton

## making connections beautifully

	Wiring Accessories	Smart Lighting Control • Wireless Audio					
<u>78C3X40</u>							
Hartland CFX Black Nickel 3x400W Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmers Black Nickel							
Item Image	Wiring	Dimensions					
		Hamilton					
		HARI LAND UFA 3X40 Resistive Leading Edge Push On-Off Rotary					
	Dimme Wining Like Neutral Like Vertral	2 Way Switching Dimmer					
		145.0					
the second se	Nete: When using as © Dw Way Generation						
	L2 terminal is not used Noze: When webching from more than one position take way demonst own of the used in conjunction with webches, i.e. only one demonst predicate.						
Drimon / Dongo	Hartland CFX						
Primary Range Insert Type	3 gang 400w Resistive Leading Edge Push On/Off Rotary 2 V	Nov Switching Dimmor					
Plate Finish	Hartland CFX Black Nickel						
Insert Colour	Black Nickel						
EAN13 Barcode	5017504289430						
Commodity Code	85365015						
Luckins TSI	388240883						
ETIM Class	EC000025						
Dimensions (Nominal)	Double: Height = 86.0mm Width = 145.0mm Depth = 5.0mm						
Fixing Hole Centres	Box Fixing = 120.6mm Grid Fixing = CFX Clips						
Minimum Wall Box Depth	35mm						
Wattage	400W per gang						
Switched Poles	Single						
Current Rating	1.66 Amps per gang						
Voltage	230V AC						
Maximum Load	400W resistive per gang						
Mains Frequency	50Hz						
IP Rating	IP2XD						
Contact Gap Minimum	N/A						
Terminal Capacity 1	2x1mm <sup>2</sup>						
Terminal Capacity 2	2x1.5mm <sup>2</sup>						
Earth Terminal Capacity 1	5x1mm <sup>2</sup>						
Earth Terminal Capacity 2	4 x 1.5mm2						
Earth Terminal Capacity 3	3 x 2.5mm2						
Earth Terminal Capacity 4	1 x 4mm2 Multi-strand						
Earth Terminal Capacity 5	1 x 6mm2						
Product Class 1	Face plate must be earthed						
Ambient Operating Temperature	-5° to +40°C						
Recommended Location	Internal Use Only						
Maximum Installation Altitude	2000m						
Standard/Approval	BS EN 60669-2-1						
Additional Notes	Tungsten filament GU10 lamps must be branded with a fuse base. When using mains voltagehalogen lamps- dimmers should be de-rated by 25%. When dimming LED lamps de-rated by 75% - please contact our Technical for compatibility.						

SL

## Hamilton

## making connections beautifully

SL

## Wiring Accessories • Smart Lighting Control • Wireless Audio

<u>78C3X40</u>

Patents and Trademarks	CFX is a Registered Trade Mark No 2398667 Hartland CFX is a Registered Design under Refe R21 = 3023446 SS2 = 3023445	erence Nos.		
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.		It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.	
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we canno guarantee an exact colour match and shading of certain finishes.		Correct as at 05 July 2022 08:55 AM E&OE	
	ad, Brislington, Bristol, BS4 5NZ ice 1 Rushmills, Bedford Road, Northampton NN4 7YB London No. 941624 VAT Registration No. 222 6607 84		Listed in Strimble	riba product selector