

making connections beautifully

Wiring Accessories • Smart Lighting Control • Wireless Audio

7CBC3XTSBK-B

Hartland CFX Copper Bronze 3 gang Multi-Way Touch Slave Controller Black Nickel/Black

Hartland CFX Co	pper Bronze 3 gang Multi-Way Touch Slave Cont	troller black Nickel/Black		
Item Image	Wiring	Dimensions Hamilton HARTLAND CFX 3XTS Multi-WayTouch Slave Controller		
	Multi-Way Wiring using Slave module(s) Multi-Way Wiring using Slave module(s) MASTER MODULE SLAVE MODULE SLAVE MODULE ONLY ONE MASTER MODULE IS USED PER CIRCUIT.			
				145.0
		Primary Range	Hartland CFX	Hartland CFX
Insert Type	3 gang Multi-Way Touch Slave Controller	3 gang Multi-Way Touch Slave Controller		
Plate Finish	Hartland CFX Copper Bronze	Hartland CFX Copper Bronze		
Insert Colour	Black Nickel/Black			
EAN13 Barcode	5017504010775	5017504010775		
Commodity Code	85363010	85363010		
Luckins TSI	398268428	398268428		
ETIM Class	EC000025	EC000025		
Dimensions (Nominal)	Double: Height = 86.0mm Width = 145.0mm Depth = 5.0	Double: Height = 86.0mm Width = 145.0mm Depth = 5.0mm		
Fixing Hole Centres	Box Fixing = 120.6mm Grid Fixing = CFX Clips	Box Fixing = 120.6mm Grid Fixing = CFX Clips		
Minimum Wall Box Depth	35mm	35mm		
Wattage	The same as Touch Master or Ceiling Dimmer	The same as Touch Master or Ceiling Dimmer		
Switched Poles	N/A	N/A		
Current Rating	The same as Touch Master or Ceiling Dimmer	The same as Touch Master or Ceiling Dimmer		
Voltage	220/250V AC	220/250V AC		
Maximum Load	The same as Touch Master	The same as Touch Master		
Mains Frequency	50Hz	50Hz		
IP Rating	IP2XD			
Contact Gap Minimum	N/A			
Terminal Capacity 1	2x1mm²			
Terminal Capacity 2	2x1.5mm²			
Earth Terminal Capacity 1	5x1mm²			
Earth Terminal Capacity 2	4 x 1.5mm2			
Earth Terminal Capacity 3	3 x 2.5mm2	3 x 2.5mm2		
Earth Terminal Capacity 4	1 x 4mm2 Multi-strand	1 x 4mm2 Multi-strand		
Earth Terminal Capacity 5	1 x 6mm2	1 x 6mm2		
Product Class 1	Face plate must be earthed	Face plate must be earthed		
Ambient Operating Temperature	-5° to +40°C			
Recommended Location	Internal Use Only	Internal Use Only		
Maximum Installation Altitude	2000m			
Standard/Approval	BS EN 60669-2-1	BS EN 60669-2-1		
Additional Notes	Tungsten filament GU10 lamps must be branded with a fuse base. When using mains voltagehalogen lamps- dimmers should be de-rated by 25%. When using mains voltage halogen load transformer - maximum rating is 210VA. To only be used with Touch Master Dimmers			



making connections beautifully

Wiring Accessories • Smart Lighting Control • Wireless Audio

7CBC3XTSBK-B

Hartland CEX Copper Bronze 3 gang Multi-Way Touch Slave Controller Black Nickel/Black

Traitiant of A copper bronze 3 gaing Multi-Way Touch Slave Controller Black Mickel/Black			
	Patents and Trademarks	CFX is a Registered Trade Mark No 2398667 Hartland CFX is a Registered Design under Reference Nos. R21 = 3023446 SS2 = 3023445	
	All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
	Illustrations and diagrams are reproduced within the limitations of reproduction and printing	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of	Correct as at 05 July 2022 08:57 AM E&OE

of certain finishes.

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088
E: info@hamilton-litestat.com www.hamilton-litestat.com

process and are not binding.

Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB Registered in London No. 941624 VAT Registration No. 222 6607 84











