

making connections beautifully

Wiring Accessories • Smart Lighting Control • Wireless Audio

7CBC4X40

Hartland CFX Copper Bronze 4x400W Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmers max 300W per gang Copper Bronze

	gang copper Bionze			
Item Image	Wiring	Dimensions		
	Dimmer Wiring Loop In Loop CNc Too Way Switching Lamp Lump Natur Warn rang as Life armed it not used Figure When multilary from more than one position as so may demore can only be used in completion with multilary from only more than one position as only one demore per croud.	Haritand CFX 4X40 Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer		
Primary Range	Hartland CFX			
Insert Type	4 gang 400W Resistive Leading Edge Push On/Off Rotary 2 Way Switching Dimmer max 300W per gang			
Plate Finish	Hartland CFX Copper Bronze	·		
Insert Colour	Copper Bronze			
EAN13 Barcode	5017504010805			
Commodity Code	85365015			
Luckins TSI	398268664	398268664		
ETIM Class	EC000025			
Dimensions (Nominal)	Double: Height = 86.0mm Width = 145.0mm Depth = 5.	Double: Height = 86.0mm Width = 145.0mm Depth = 5.0mm		
Weight	325 GR			
Fixing Hole Centres	Box Fixing = 120.6mm Grid Fixing = CFX Clips	Box Fixing = 120.6mm Grid Fixing = CFX Clips		
Minimum Wall Box Depth	35mm			
Wattage	300W per gang			
Switched Poles	Single			
Current Rating	1.25 Amps per gang			
Voltage	230V AC			
Maximum Load	300W resistive per gang			
Mains Frequency	50Hz			
IP Rating	IP2XD			
Contact Gap Minimum	N/A			
Terminal Capacity 1	2x1mm²			
Terminal Capacity 2	2x1.5mm²			
Earth Terminal Capacity 1	5x1mm²			
Earth Terminal Capacity 2	4 x 1.5mm2			
Earth Terminal Capacity 3	3 x 2.5mm2	3 x 2.5mm2		
Earth Terminal Capacity 4	1 x 4mm2 Multi-strand	1 x 4mm2 Multi-strand		
Earth Terminal Capacity 5	1 x 6mm2			
Product Class 1	Face plate must be earthed	Face plate must be earthed		
Ambient Operating Temperature	-5° to +40°C	-5° to +40°C		
Recommended Location	Internal Use Only	Internal Use Only		
Maximum Installation Altitude	2000m			
Standard/Approval	BS EN 60669-2-1			
Additional Notes	Tungsten filament GU10 lamps must be branded with a fuse base. When using mains voltagehalogen lamps- dimmers should be de-rated by 25%. When dimming LED lamps de-rated by 75% - please contact our Technical for compatibility.			



making connections beautifully

Wiring Accessories • Smart Lighting Control • Wireless Audio

7CBC4X40

Hartland CFX Copper Bronze 4x400W Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmers max 300W per gang Copper Bronze

	gang copper bronze		
	Patents and Trademarks	CFX is a Registered Trade Mark No 2398667 Hartland CFX is a Registered Design under Reference Nos. R21 = 3023446 SS2 = 3023445	
	All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
	Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.	Correct as at 05 July 2022 08:57 AM E&OE

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088
E: info@hamilton-litestat.com www.hamilton-litestat.com

Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB Registered in London No. 941624 VAT Registration No. 222 6607 84









