



making connections beautifully

Wiring Accessories • Smart Lighting Control • Wireless Audio

7HBCWRRTBL-B

Hartland CFX Connaught Bronze Wide Rocker 1 gang 10AX Push To Make/Push to Break Retractive XX-Black

| Hartland CFX Connaught Bronze Wide Rocker 1 gang 10AX Push To Make/Push to Break Retractive XX-Black | | | |
|--|---|------------|--|
| Item Image | Wiring | Dimensions | |
| _ | _ | | |
| | × | × | |
| | | | |
| | | | |
| | | | |
| | | | |
| | | | |
| | | | |
| | | | |
| | | | |
| | | | |
| Drivers | Under d. OFV | | |
| Primary Range Insert Type | Hartland CFX Wide Rocker - 1 gang 10AX Push To Make/Push to Break Retractive Rocker | | |
| Plate Finish | Wide Rocker - 1 gang 10AX Push 10 Make/Push to Break Retractive Rocker Hartland CFX Connaught Bronze | | |
| Insert Colour | Black/Black | | |
| EAN13 Barcode | 5051164021467 | | |
| Commodity Code | 85363010 | | |
| Luckins TSI | 453341419 | | |
| ETIM Class | EC001590 | | |
| Dimensions (Nominal) | Single: Height = 86.0mm Width = 86.0mm Depth = 5.0mm | | |
| Fixing Hole Centres | Box Fixing = 60.3mm Grid Fixing = CFX Clips | | |
| Minimum Wall Box Depth | 25mm | | |
| Switched Poles | Single | | |
| Current Rating | 10AX | | |
| Voltage | 220/250V AC | | |
| Maximum Load | 10 Amp inductive | | |
| Mains Frequency | 50Hz | | |
| IP Rating | IP2XD | | |
| Contact Gap Minimum | 3mm | | |
| Terminal Capacity 1 | 3x2.5mm ² | | |
| Terminal Capacity 2 | 1x4mm² Multi-strand | | |
| Terminal Capacity 3 | 1x6mm² | | |
| Earth Terminal Capacity 1 | 6x1mm² | | |
| Earth Terminal Capacity 2 | 4x1.5mm² | | |
| Earth Terminal Capacity 3 | 2x2.5mm² | | |
| Earth Terminal Capacity 4 | 1x4mm² Multi-strand | | |
| Earth Terminal Capacity 5 | 1x6mm² | | |
| Product Class 1 | Must be earthed | | |
| Ambient Operating Temperature | -5° to +40°C | | |
| Recommended Location | Internal Use Only | | |
| Maximum Installation Altitude | 2000m | | |
| Standard/Approval | BS EN 60669-1 | | |
| Additional Notes | CE Marked | | |
| Module Size | Height = 67mm Width = 67mm Depth = 22mm | | |



making connections beautifully

Wiring Accessories • Smart Lighting Control • Wireless Audio

7HBCWRRTBL-B

Hartland CFX Connaught Bronze Wide Rocker 1 gang 10AX Push To Make/Push to Break Retractive XX-Black

| | 5 5 | |
|---|--|--|
| Patents and Trademarks | CFX is a Registered Trade Mark No 2398667 Hartland CFX is a Registered Design under Reference Nos. R21 = 3023446 SS2 = 3023445 | |
| All products listed conform to current British or European standard and the product information is correct at the time of going to press. | All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System. | It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice. |
| Illustrations and diagrams are reproduced within | Due to manufacturing processes we cannot | Correct as at 05 July 2022 08:59 AM |

of certain finishes.

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088
E: info@hamilton-litestat.com www.hamilton-litestat.com

process and are not binding.

Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB Registered in London No. 941624 VAT Registration No. 222 6607 84









