




71CDTRIDW

Hartland CFX Polished Brass Non-Isolated TV+FM+SAT Triplexer 1in/3out (DAB Compatible) White

| Item Image | Wiring | Dimensions |
|---|---|---|
|  |  <p>1. Undo the cable clamp screw. 2. Lift up the cover of the clamp, be careful not to displace the EMC gasket which is located on the cover. 3. Insert the conductor into the terminal slot which is located in the casing of the module. 4. Before closing the cover check to ensure that conductor, screening braid and cable are in the correct position as shown below. 5. Carefully close the cover of the module ensuring that the EMC gasket is not displaced or damaged. Then tighten the cable clamp screw.</p> |  |
| Primary Range | Hartland CFX | |
| Insert Type | Non-Isolated TV+FM+SAT Triplexer 1in/3out (DAB Compatible) | |
| Plate Finish | Hartland CFX Polished Brass | |
| Insert Colour | White | |
| EAN13 Barcode | 5017504009212 | |
| Commodity Code | 85367000 | |
| Luckins TSI | 391428618 | |
| ETIM Class | EC000439 | |
| Dimensions (Nominal) | Single: Height = 86.0mm Width = 86.0mm Depth = 5.0mm | |
| Fixing Hole Centres | Box Fixing = 60.3mm Grid Fixing = CFX Clips | |
| Minimum Wall Box Depth | 35mm | |
| Switched Poles | N/A | |
| Current Rating | n/a | |
| IP Rating | IP2XD | |
| Contact Gap Minimum | N/A | |
| Earth Terminal Capacity 1 | 5x1mm ² | |
| Earth Terminal Capacity 2 | 4 x 1.5mm ² | |
| Earth Terminal Capacity 3 | 3 x 2.5mm ² | |
| Earth Terminal Capacity 4 | 1 x 4mm ² Multi-strand | |
| Earth Terminal Capacity 5 | 1 x 6mm ² | |
| Product Class 1 | Must be earthed (ref BS7671 415.2.1) | |
| Ambient Operating Temperature | -5° to +40°C | |
| Recommended Location | Internal Use Only | |
| Maximum Installation Altitude | 2000m | |
| Standard/Approval | BS EN 50083-2:2012/A1; 2015. BS EN 61169-2:2007. BS EN 61169-24:2009 | |
| EuroFix Additional Notes | Triplexer for use with combined TV FM and Satellite Signal (DAB compatible) | |
| Frequencies 1 | TV=5-68 MHz 125-860 MHz | |
| Frequencies 2 | FM=88-108 MHz | |
| Frequencies 3 | SAT DC=950-2200 MHz | |
| Patents and Trademarks | CFX is a Registered Trade Mark No 2398667 Hartland CFX is a Registered Design under Reference Nos. R21 = 3023446 SS2 = 3023445 | |
| All products listed conform to current British or European standard and the product information is correct at the time of going to press. | All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System. | |
| It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice. | Correct as at 05 July 2022 08:49 AM E&OE | |
| Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding. | Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes. | |