

making connections beautifully

Wiring Accessories • Smart Lighting Control • Wireless Audio

7RBC1X2V

Hartland CFX Richmond Bronze 1 gang 200VA Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer Richmond
Bronze

	Bronze		
Item Image	Wiring	Dimensions	
	LOOF IN LOOP CUT TWO MAY SMITCHING MICHAEL STATE OF THE MAY SMITCHING MICHAEL STATE OF THE MAY SMITCHING LOOF IN LOOP CUT TWO MAY SMITCHING MICHAEL STATE OF THE MAY SMITCHING LOOF IN LOOP CUT TWO MAY SMITCHING LOOF IN LOOP CUT TWO MAY SMITCHING LOOP IN LOOP CUT TWO MAY SMITCHING LOOF CUT TWO M	HEMILON HARTLAND CFX 1/2V Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer	
Primary Range	Hartland CFX		
Insert Type	1 gang 200VA Inductive Leading Edge Push On/Off Rotary 2	1 gang 200VA Inductive Leading Edge Push On/Off Rotary 2 Way Switching Dimmer	
Plate Finish	Hartland CFX Richmond Bronze		
Insert Colour	Richmond Bronze		
EAN13 Barcode	5017504014216		
Commodity Code	85365015		
Luckins TSI	398319241		
ETIM Class	EC000025		
Dimensions (Nominal)	Single: Height = 86.0mm Width = 86.0mm Depth = 5.0mm		
Fixing Hole Centres	Box Fixing = 60.3mm Grid Fixing = CFX Clips		
Minimum Wall Box Depth	35mm		
Wattage	200VA (low voltage)		
Switched Poles	Single		
Current Rating	0.8 Amp		
Voltage	220/250V AC		
Maximum Load	200VA (low voltage) Min Load 25VA		
Mains Frequency	50Hz		
IP Rating	IP2XD		
Contact Gap Minimum	None		
Terminal Capacity 1	2x1mm²		
Terminal Capacity 2	2x1.5mm²		
Earth Terminal Capacity 1	5x1mm²		
Earth Terminal Capacity 2	4 x 1.5mm2		
Earth Terminal Capacity 3	3 x 2.5mm2		
Earth Terminal Capacity 4	1 x 4mm2 Multi-strand		
Earth Terminal Capacity 5	1 x 6mm2		
Product Class 1	Face plate must be earthed		
Ambient Operating Temperature	-5° to +40°C		
Recommended Location	Internal Use Only	Internal Use Only	
Maximum Installation Altitude	2000m		
Standard/Approval	BS EN 60669-1	BS EN 60669-1	
Additional Notes	LEADING EDGE TECHNOLOGY DIMMERS for use with low voltage toroidal transformers and some LED lamps. When dimming LED lamps de-rated by 75% - please contact our Technical for compatibility. NOTE:It is recommended to contact the manufacturer of the transformer to confirm that it is dimmable and is considered to be an inductive load.		



making connections beautifully

Wiring Accessories • Smart Lighting Control • Wireless Audio

7RBC1X2V

Hartland CFX Richmond Bronze 1 gang 200VA Inductive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer Richmond

5101120		
Patents and Trademarks	CFX is a Registered Trade Mark No 2398667 Hartland CFX is a Registered Design under Reference Nos. R21 = 3023446 SS2 = 3023445	
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.	Correct as at 05 July 2022 09:01 AM E&OE

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088 E: info@hamilton-litestat.com www.hamilton-litestat.com

Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB Registered in London No. 941624 VAT Registration No. 222 6607 84









