

making connections beautifully

Wiring Accessories • Smart Lighting Control • Wireless Audio

7RBC2XTSBK-B

Hartland CFX Richmond Bronze 2 gang Multi-Way Touch Slave Controller Black Nickel/Black

Item Image	Wiring	Dimensions	
	Multi-Way Wiring using Slave module(s) Multi-Way Wiring using Slave module(s) List Slave Module Slave Module Slave Module MASTER MODULE SLAVE MODULE SLAVE MODULE ONLY ONE MASTER MODULE IS USED PER GIRCUIT.	Hamilton HARTLAND CFX 2XTS Multi-WayTouch Slave Controller	
Primary Range	Hartland CFX		
Insert Type	2 gang Multi-Way Touch Slave Controller	2 gang Multi-Way Touch Slave Controller	
Plate Finish	Hartland CFX Richmond Bronze		
Insert Colour	Black Nickel/Black	Black Nickel/Black	
EAN13 Barcode	5017504078034	5017504078034	
Commodity Code	85363010	85363010	
Luckins TSI	403394229	403394229	
ETIM Class	EC000025	EC000025	
Dimensions (Nominal)	Single: Height = 86.0mm Width = 86.0mm Depth = 5.0n	Single: Height = 86.0mm Width = 86.0mm Depth = 5.0mm	
Fixing Hole Centres	Box Fixing = 60.3mm Grid Fixing = CFX Clips		
Minimum Wall Box Depth	35mm	35mm	
Wattage	The same as Touch Master or Ceiling Dimmer	The same as Touch Master or Ceiling Dimmer	
Switched Poles	N/A		
Current Rating	The same as Touch Master or Ceiling Dimmer	The same as Touch Master or Ceiling Dimmer	
Voltage	220/250V AC		
Maximum Load	The same as Touch Master	The same as Touch Master	
Mains Frequency	50Hz	50Hz	
IP Rating	IP2XD	IP2XD	
Contact Gap Minimum	N/A	N/A	
Terminal Capacity 1	2x1mm²		
Terminal Capacity 2	2x1.5mm²	2x1.5mm ²	
Earth Terminal Capacity 1	5x1mm²	5x1mm²	
Earth Terminal Capacity 2	4 x 1.5mm2	4 x 1.5mm2	
Earth Terminal Capacity 3	3 x 2.5mm2		
Earth Terminal Capacity 4	1 x 4mm2 Multi-strand	1 x 4mm2 Multi-strand	
Earth Terminal Capacity 5	1 x 6mm2	1 x 6mm2	
Product Class 1	Face plate must be earthed	Face plate must be earthed	
Ambient Operating Temperature	-5° to +40°C		
Recommended Location	Internal Use Only		
Maximum Installation Altitude	2000m	2000m	
Standard/Approval	BS EN 60669-2-1		
Additional Notes		Tungsten filament GU10 lamps must be branded with a fuse base. When using mains voltagehalogen lamps- dimmers should be de-rated by 25%. When using mains voltage halogen load transformer - maximum rating is 210VA. To only be used with Touch Master Dimmers	



making connections beautifully

Wiring Accessories • Smart Lighting Control • Wireless Audio

7RBC2XTSBK-B

Hartland CFX Richmond Bronze 2 gang Multi-Way Touch Slave Controller Black Nickel/Black				
Patents and Trademarks	CFX is a Registered Trade Mark No 2398667 Hartland CFX is a Registered Design under Reference Nos. R21 = 3023446 SS2 = 3023445			
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.		
Illustrations and diagrams are reproduced within	Due to manufacturing processes we cannot	Correct as at 05 July 2022 09:01 AM		

of certain finishes.

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088
E: info@hamilton-litestat.com www.hamilton-litestat.com

process and are not binding.

Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB Registered in London No. 941624 VAT Registration No. 222 6607 84









