



## 7RBCDENTB

### Hartland CFX Richmond Bronze Non-Isolated TV+FM+SAT1+SAT2 Quadplexer 2in/4out (DAB Compatible) Black

Item Image	Wiring	Dimensions
	 <ol style="list-style-type: none"> <li>1. Undo the cable clamp screw.</li> <li>2. Lift up the cover of the clamp, be careful not to displace the EMC gasket which is located on the cover.</li> <li>3. Insert the conductor into the terminal slot which is located in the casing of the module.</li> <li>4. Before closing the cover check to ensure that conductor, screening braid and cable are in the correct position as shown below.</li> <li>5. Carefully close the cover of the module ensuring that the EMC gasket is not displaced or damaged. Then tighten the cable clamp screw.</li> </ol>	 <p>Hamilton® HARTLAND CFX DENT Non-Isolated TV/FM/Satellite1/Satellite2 Quadplexer 2in/4out</p>
Primary Range	Hartland CFX	
Insert Type	Non-Isolated TV+FM+SAT1+SAT2 Quadplexer 2in/4out (DAB Compatible)	
Plate Finish	Hartland CFX Richmond Bronze	
Insert Colour	Black	
EAN13 Barcode	5017504014483	
Commodity Code	85367000	
Luckins TSI	398319746	
ETIM Class	EC000439	
Dimensions (Nominal)	Single: Height = 86.0mm Width = 86.0mm Depth = 5.0mm	
Fixing Hole Centres	Box Fixing = 60.3mm Grid Fixing = CFX Clips	
Minimum Wall Box Depth	35mm	
Switched Poles	N/A	
Current Rating	n/a	
IP Rating	IP2XD	
Contact Gap Minimum	N/A	
Earth Terminal Capacity 1	5x1mm <sup>2</sup>	
Earth Terminal Capacity 2	4 x 1.5mm <sup>2</sup>	
Earth Terminal Capacity 3	3 x 2.5mm <sup>2</sup>	
Earth Terminal Capacity 4	1 x 4mm <sup>2</sup> Multi-strand	
Earth Terminal Capacity 5	1 x 6mm <sup>2</sup>	
Product Class 1	Must be earthed (ref BS7671 415.2.1)	
Ambient Operating Temperature	-5° to +40°C	
Recommended Location	Internal Use Only	
Maximum Installation Altitude	2000m	
Standard/Approval	BS EN 50581:2012, BS EN 60728-4:2008, BS EN 50083-2: 2012/A1:2015	
EuroFix Additional Notes	Quadplexer for use with combined TV FM and Satellite Signals (DAB compatible)	
Frequencies 1	TV=5-68 MHz 125-860 MHz	
Frequencies 2	FM=88-108 MHz	
Frequencies 3	SAT DC=950-2200 MHz	
Patents and Trademarks	CFX is a Registered Trade Mark No 2398667 Hartland CFX is a Registered Design under Reference Nos. R21 = 3023446 SS2 = 3023445	
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	
It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.	Correct as at 05 July 2022 09:01 AM E&OE	
Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding.	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes.	