

making connections beautifully

Wiring Accessories • Smart Lighting Control • Wireless Audio

70C1XTE

	A Resistive/Inductive Trailing Edge Push On/Off Rotary Multi-Way Dimmer Gloss Whit		
Item Image	Wiring Dimensions		
	Hemilton* HARTLAND CFX 1XTE Multi-Way Wiring uning Retractive PTM Rocker Switches Resistive/Inductive Trailing Edge Push On/Off		
	Rotary Multi-Way Dimmer Rotary Multi-Way Dimmer 86.0 86.0 86.0 Rotary Multi-Way Dimmer 86.0		
Primary Range	Hartland CFX		
Insert Type	1 gang 250W/210VA Resistive/Inductive Trailing Edge Push On/Off Rotary Multi-Way Dimmer		
Plate Finish	Hartland CFX Gloss White		
Insert Colour	Gloss White		
EAN13 Barcode	5017504008413		
Commodity Code	85365015		
Luckins TSI	398263070		
ETIM Class	EC000025		
Dimensions (Nominal)	Single: Height = 86.0mm Width = 86.0mm Depth = 5.0mm		
Fixing Hole Centres	Box Fixing = 60.3mm Grid Fixing = CFX Clips		
Minimum Wall Box Depth	35mm		
Wattage	250W Resistive 210VA Inductive		
Switched Poles	Single		
Current Rating	1.1 Amp		
Voltage	220/250V AC		
Maximum Load	250W Resistive 210VA Inductive Min Load 25W/25VA		
Mains Frequency	50Hz		
IP Rating	IP2XD		
Contact Gap Minimum	None		
Terminal Capacity 1	2x1mm²		
Terminal Capacity 2	2x1.5mm²		
Earth Terminal Capacity 1	5x1mm²		
Earth Terminal Capacity 2	4 x 1.5mm2		
Earth Terminal Capacity 3	3 x 2.5mm2		
Earth Terminal Capacity 4	1 x 4mm2 Multi-strand		
Earth Terminal Capacity 5	1 x 6mm2		
Product Class 1	Face plate must be earthed		
Ambient Operating Temperature	-5° to +40°C		
Recommended Location	Internal Use Only		
Maximum Installation Altitude	2000m		
Standard/Approval	BS EN 60669-2-1		
Additional Notes	TRAILING EDGE TECHNOLOGY DIMMERS. Are suitable for control of both resistive and inductive loads. When used for dimming low voltage electronic halogen transformers it must be noted that the dimmer controls the primary side of the transformer. Tungsten filament GU10 lamps must be branded with a fuse base. When using mains voltagehalogen lamps-dimmers should be de-rated by 25%. When dimming LED lamps de-rated by 75% - please contact our Technical for compatibility. When using mains voltage halogen load transformer - maximum rating is 210VA. NOTE: For multi-way switching a push to make retractive switch should be installed in the other positions. (Note:standard two way switches will not work with this product)		



SL

making connections beautifully

Wiring Accessories • Smart Lighting Control • Wireless Audio

70C1XTE

Hartland CFX Gloss White 1x250W/210VA Resistive/Inductive Trailing Edge Push On/Off Rotary Multi-Way Dimmer Gloss White

	5 5	•
Patents and Trademarks	CFX is a Registered Trade Mark No 2398667 Hartland CFX is a Registered Design under Reference Nos. R21 = 3023446 SS2 = 3023445	
All products listed conform to current British or European standard and the product information is correct at the time of going to press.	All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System.	It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice.
Illustrations and diagrams are reproduced within the limitations of reproduction and printing	Due to manufacturing processes we cannot guarantee an exact colour match and shadings of	Correct as at 05 July 2022 08:48 AM E&OE

R Hamilton & Co Ltd, Unit 10 Carrick Business Centre, 4-5 Bonville Road, Brislington, Bristol, BS4 5NZ

T: +44 (0)1747 860088

E: info@hamilton-litestat.com www.hamilton-litestat.com

Registered Office 1 Rushmills, Bedford Road, Northampton NN4 7YB Registered in London No. 941624 VAT Registration No. 222 6607 84









