Hamilton

making connections beautifully

SL

| | Wiring Accessories | Smart Lighting Control • Wireless Audio | | |
|---|---|---|--|--|
| 7WPC4X40 | | | | |
| | | | | |
| Hartland CFX Primed White 4x400W Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmers max 300W per gang White | | | | |
| Item Image | Wiring | Dimensions | | |
| | | Hamilton | | |
| | | | | |
| | Dimmer Wiring Loop In Loop Out: Two Way Switching | 4X40 Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmer | | |
| | Like Neutral Like Neutral | | | |
| | 608 | | | |
| | | 145.0 | | |
| | | | | |
| | Note: When using as a Dre Way Demoner the L3 terminal in not used. | | | |
| | used in conjunction with waikches. In, only one demonstrate circuit. | | | |
| | | | | |
| | | | | |
| Primary Range | Hartland CFX | | | |
| Insert Type | 4 gang 400W Resistive Leading Edge Push On/Off Rotary 2 Way Switching Dimmer max 300W per gang | | | |
| Plate Finish | Hartland CFX Primed White | | | |
| Insert Colour | White | | | |
| EAN13 Barcode | 5017504015145 | | | |
| Commodity Code | 85365015 | | | |
| Luckins TSI | 398331847 | | | |
| ETIM Class | EC000025 | | | |
| Dimensions (Nominal) | Double: Height = 86.0mm Width = 145.0mm Depth = 5.0mm | | | |
| Weight | 325 GR | | | |
| Fixing Hole Centres | Box Fixing = 120.6mm Grid Fixing = CFX Clips | | | |
| Minimum Wall Box Depth | 35mm | | | |
| Wattage | 300W per gang | | | |
| Switched Poles | Single | | | |
| Current Rating | 1.25 Amps per gang | | | |
| Voltage | 230V AC | | | |
| Maximum Load | 300W resistive per gang | | | |
| Mains Frequency | 50Hz | | | |
| IP Rating | IP2XD | | | |
| Contact Gap Minimum | N/A | | | |
| Terminal Capacity 1 | 2x1mm ² | | | |
| Terminal Capacity 2 | 2x1.5mm ² | | | |
| Earth Terminal Capacity 1 | 5x1mm ² | | | |
| Earth Terminal Capacity 2 | 4 x 1.5mm2 | | | |
| Earth Terminal Capacity 3 | 3 x 2.5mm2 | | | |
| Earth Terminal Capacity 4 | 1 x 4mm2 Multi-strand | | | |
| Earth Terminal Capacity 5 Product Class 1 | 1 x 6mm2 | | | |
| Ambient Operating Temperature | Face plate must be earthed | | | |
| Recommended Location | -5° to +40°C | | | |
| Recommended Location Maximum Installation Altitude | Internal Use Only 2000m | | | |
| Standard/Approval | BS EN 60669-2-1 | | | |
| | Tungsten filament GU10 lamps must be branded with a fuse base. When using mains voltagehalogen lamps- dimmers | | | |
| Additional Notes | should be de-rated by 25%. When dimming LED lamps de-rated by 75% - please contact our Technical for compatibility. | | | |

Hamilton

making connections beautifully

CERT. No. FM11238

Wiring Accessories • Smart Lighting Control • Wireless Audio

7WPC4X40

Hartland CFX Primed White 4x400W Resistive Leading Edge Push On-Off Rotary 2 Way Switching Dimmers max 300W per gang White

| 0 0 | | |
|---|---|--|
| Patents and Trademarks | CFX is a Registered Trade Mark No 2398667 Hartland CFX is a Registered Design under Reference N R21 = 3023446 SS2 =3023445 | os. |
| All products listed conform to current British or European standard and the product information is correct at the time of going to press. | All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System. | It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice. |
| Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding. | Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes. | Correct as at 05 July 2022 09:02 AM E&OE |
| | ad, Brislington, Bristol, BS4 5NZ ice 1 Rushmills, Bedford Road, Northampton NN4 7YB ordon No. 941624 (Vat Benistration No. 222 6607.84 | Listed in Strimble product Product Selector |

SL