Hamilton

making connections beautifully

| Wiring Accessories • Smart Lighting Control • Wireless Audio | | | |
|---|---|---------------------|--|
| 7EBCR26BL-B | | | |
| Hartland CFX Etrium Bronze 6 gang 10AX 2 Way Rocker Black/Black | | | |
| | Central Bronze o gang to ix 2 way Rooke | | |
| Item Image | Wiring | Dimensions | |
| | Image: second | | |
| | | R26 2 Way Rocker | |
| | | | |
| | | | |
| Primary Range | Hartland CFX | | |
| Insert Type | 6 gang 10AX 2 Way Rocker | | |
| Plate Finish | Hartland CFX Etrium Bronze | | |
| Insert Colour | Black/Black | | |
| EAN13 Barcode | 5017504012090 | | |
| Commodity Code | 85363010 | | |
| Luckins TSI | 398274263 | | |
| ETIM Class | EC001590 | | |
| Dimensions (Nominal) | Double: Height = 86.0mm Width = 145.0mm Depth = 5.0mm | | |
| Weight | 332 GR | | |
| Fixing Hole Centres | Box Fixing = 120.6mm Grid Fixing = CFX Clips | | |
| Minimum Wall Box Depth | 25mm | | |
| Switched Poles | Single | | |
| Current Rating | 10AX | | |
| Voltage | 220/250V AC | | |
| Maximum Load | 10 Amp inductive | | |
| Mains Frequency | 50Hz | | |
| IP Rating | IP2XD | | |
| Contact Gap Minimum | 3mm | | |
| Terminal Capacity 1 | 5x1mm ² | | |
| Terminal Capacity 2 | 4x1.5mm ² | | |
| Terminal Capacity 3 | 1x2.5mm ² | | |
| Terminal Capacity 4 | 1x4mm ² Multi-strand | | |
| Terminal Capacity 5 | 1x6mm ² | | |
| Earth Terminal Capacity 1 | 5x1mm ² | | |
| Earth Terminal Capacity 2 | 4x1.5mm ² | | |
| Earth Terminal Capacity 3 | 3x2.5mm ² | | |
| Earth Terminal Capacity 4 | 1x4mm ² Multi-strand | | |
| Earth Terminal Capacity 5 | 1x6mm ² | | |
| Product Class 1 | Must be earthed | | |
| Ambient Operating Temperature | -5° to +40°C | | |
| Recommended Location | Internal Use Only | | |
| Maximum Installation Altitude | 2000m | | |
| Standard/Approval | BS EN 60669-1 | | |

SL

Hamilton

making connections beautifully

| Wiring Accessories • Smart Lighting Control • Wireless Audio | | | |
|---|--|--|--|
| 7EBCR26BL-B | | | |
| Hartland CFX Etrium Bronze 6 gang 10AX 2 Way Rocker Black/Black | | | |
| Patents and Trademarks | CFX is a Registered Trade Mark No 2398667 Hartland CFX is a Registered Design under Reference Nos. R21 = 3023446 SS2 = 3023445 | | |
| All products listed conform to current British or European standard and the product information is correct at the time of going to press. | All accessories are manufactured under an accredited BS EN ISO 9001 : 2015 Quality Management System. | It is the policy of the company to improve products as part of our development programme. Therefore, we reserve the right to alter designs and dimensions without prior notice. | |
| Illustrations and diagrams are reproduced within the limitations of reproduction and printing process and are not binding. | Due to manufacturing processes we cannot guarantee an exact colour match and shadings of of certain finishes. | Correct as at 05 July 2022 08:58 AM E&OE | |
| | ad, Brislington, Bristol, BS4 5NZ fice 1 Rushmills, Bedford Road, Northampton NN4 7YB London No. 941624 VAT Registration No. 222 6607 84 | Listed in Strimbe LUCKINS relector DSSPUs (LIST No. 1128) | |

SL